

How to configure a serial PPP connection in Windows 7

PRIMUS Solution emc257433 W/ FULL STEP BY STEP PROCEDURE INCLUDED BELOW

ID: emc257433

Domain: EMC1

Solution Class: 3.X Compatibility

Goal **How to configure a serial PPP connection in Windows 7**

Fact Product: VNX series

Fact Product: CLARiiON CX4 series

Fact Product: CLARiiON CX3 series

Fact Product: CLARiiON CX series

Fact Product: CLARiiON AX series

Fact Product: Celerra

Fact OS: Microsoft Windows 7

Fix **First, create the COM port modem**

1. Click Start -> Control Panel -> Phone and Modem.
2. Click Modem Tab and click add.
3. On the Install new Modem Pane, select the "Don't detect my modem" box, then click Next
4. There will be a pause while it loads the models. Select Communications cable between two computers, then click Next.
5. Select your COM port, click Next and it is done.

Next, to set up the PPP connection

1. Click Start -> Control Panel -> Network and sharing center, click Set up a new connection or network (at the bottom).
2. On the next screen, select set up a dial-up connection and click Next.
3. The next screen should list modems and select the "Communications cable between two computers" you created above.
4. On the next screen do not put a phone number in, but put in the username and password (clariion and clariion!) and give it a name.
5. The above connection should now appear in Network Connections, right-click it and select Properties.

Once the connection is set up, modify the settings as follows:


1. In the General tab, click configure and set Max speed to 115200 and select enable hardware flow control.
2. In the Options tab, click PPP settings and check top two boxes are selected (LCP extensions and SW compression).
3. In the Security tab, check Data Encryption is "Optional Encryption (connect even if no encryption)" is set.
4. In the Networking tab, check Internet Protocol Version 4 is selected.
5. In the Networking tab, choose Internet Protocol Properties, then the Advanced button. Uncheck "Use default gateway on remote network."

Your connection can then be accessed from Network Connections

See below for a Step by Step guide with screenshots to assist you with setting up your WIN 7 PPP connection:

Configuring a PPP connection in Windows 7

When using a “USB to Serial cable”, check that the port is correctly recognized and note down the COM port number. Please, be aware that the “USB to Serial cable” may get a different COM port number assignment each time it is used.




You may check this in “Computer Management” .

To set up the PPP connection perform the following steps:

Open the **Control Panel**. Search for “**Phone**”




Select **Phone and Modem**, choose the **Modems** tab & click **add**




On the Install New Modem Pane select the **Don't detect my modem ...** box, then click next




There will be a pause while it loads the models, select **Communications cable between two computers**, then click **Next** to continue.




Select the COM port you want to use, click **Next** and **Finish**.




Open the **Control Panel**. Search for "Phone"




In the **Modems** tab select the **Communications cable ...** and choose **Properties**




Select **Change settings**.



In the **Modem** tab, change the **Maximum Port Speed** to **115200** and press OK.



Next, open the **Control Panel**. Search for “**Network**” and select **Set up a dial-up connection**.



NOTE: You will select “Network and Sharing Center”. If all options are not presented as shown to the left, select:

- 1) “Set up a Connection or Network”
- 2) Choose: Set up a dial-up connection

Enter the following:


Dial-up phone number: 0

User name: clariion


Password: clariion!

Connection name: Clariion PPP Connection

Click **Connect** to continue.



The host is trying to connect, but fails. (This is intended) Select **Set up the connection anyway** and **close** to continue.




Select **View network connections**



NOTE: You may need to select: "Change adapter settings" if all options are not presented like the current screenshot to the left.

Right click on the **Clariion PPP Connection** and select **Cancel as Default Connection**.




You can also name it or rename it at this time.

Right click on the **Clariion PPP Connection** and select **Properties**.

Delete the **"0"** in the **Phone number** area in the **General** tab. (Here still shown to find the location)

Deselect the **prompt for phone number** in the **Options** tab.


Deselect the **Internet Protocol Version 6** in the **Networking** tab. Click **OK** to save the changes.



Right click on the **CLARiiON PPP Connection** once again and select **Properties**

Select **Communication cable between two computers** and click on **Configure**

Set the speed to **115200** Click **OK**. Then Click **OK** again!



To connect to a Clariion or VNX for Block double click the **Clariion PPP Connection**. Enter User name: **clariion** and password: **clariion!** and press **Dial**.



REMEMBER!!! When using a “USB to Serial cable”, check that the port is correctly recognized and note down the COM port number. → Please, be aware that the “USB to Serial cable” may get a different COM port number assignment each time it is used. ←

Copyright © 2011 EMC Corporation. All rights reserved

The information in this publication is accurate as of its publication date. The information is subject to change without notice. The information is CONFIDENTIAL and it is meant to be used only internally.